FARADAY
TECHNOLOGY, INC.

Multiphysics Modeling of the Tertiary Current Distribution in Pulse/Pulse-Reverse Electrochemical Processing of Microstructured Workpieces

Brian Skinn^a, Alan C. West^b

^a Faraday Technology, Inc., Englewood, OH, USA 45315

^b School of Engineering and Applied Science, Columbia Univ., New York, NY, USA 10027

14 Oct 2019

BrianSkinn@FaradayTechnology.com

Outline

- Mass-Transfer Limitations in Electrochemical Surface Finishing
 - Direct Current (Jacquet)
 - Pulsed-Current
- COMSOL® Simulations
 - 2-D System
 - Empirical 'Surface-Occlusion' Model

Conventional Electrochemical Surface Finishing

On some scale - All surfaces are rough:

→ preferential removal of asperities ←

Traditional ElectroFinishing:

1. Smooth, bright surface finish achieved under diffusion limited conditions†
→ Viscous/concentrated acid electrolytes
2. For passive materials, electrolytes designed to mitigate oxide formation
→ Oxide removal with fluoride or hydrofluoric acid (HF)
→ Non-aqueous to prevent oxide formation – not industrially practical

† P.A. Jacquet, *Trans. Electrochem. Soc.*, **69** 629 (1936).

ElectroFinishing – Direct Current (DC)

- Rectification:
 - DC - Constant voltage
 - Viscous salt film per Jacquet
 - Passive (oxide) film formation
- Electrolyte:
 - Concentrated/viscous acid
 - Chilled to increase viscosity
 - HF add to remove oxide

† P.A. Jacquet, *Trans. Electrochem. Soc.*, **69** 629 (1936).

ElectroFinishing – Pulsed Waveforms

ElectroFinishing – Pulsed Waveforms

P/PR Waveform Sequencing – SS316 Tubes

- Pulse/Pulse Reverse
 - Initial $R_a \sim 1\mu\text{m}$
 - Waveform #1
 - ➔ Short forward pulses
 - ➔ Reverse (cathodic) pulses
 - After 30 s: $R_a \sim 0.2\mu\text{m}$
 - Waveform #2
 - ➔ Long forward pulses
 - ➔ Reverse (cathodic) pulses
 - After additional 15 s: $R_a \sim 0.05\mu\text{m}$

P/PR Waveform Sequencing – AM Ti Alloy

Initial Trial

Waveforms #1 & #2 → 555 μm material removed for R_a/R_z of 1.8/12 μm

Improved Waveform Sequence

P/PR Waveform Sequencing – AM Hastelloy-X

➤ **CHALLENGE:** improve R_a to 2 μm while minimizing material removal

▪ **Waveform 1:**

- Initial rapid $\Delta R_a / \Delta \text{material removed}$ until $\sim 6 \mu\text{m}$ R_a reached
- Decrease in $\Delta R_a / \Delta \text{material removed}$ after $\sim 6 \mu\text{m}$ R_a reached

▪ **Waveform 2:**

- Initially slow $\Delta R_a / \Delta \text{material removed}$ until $\sim 6 \mu\text{m}$ R_a reached
- Increase in $\Delta R_a / \Delta \text{material removed}$ after $R_a < 6 \mu\text{m}$

➤ **SOLUTION:** Initiate process with Waveform 1 (4 min) until $R_a \sim 6 \mu\text{m}$, then switch to Waveform 2 (1 min) until next critical $R_a \sim 1.8$ with 80 μm removed.

➔ Tune process by waveform sequencing in order to achieve desired surface finish while minimizing material removal ←

FARADAY TECHNOLOGY, INC.

COMSOL[®] Simulations

Physical Phenomena in Electrochemical Processes

- Primary Current Distribution
 - *Laplace equation (Ohmic/resistive potentials)*
 - *Equilibrium reaction potentials*
- Secondary Current Distribution
 - *Kinetic polarization (Butler-Volmer/Tafel)*
 - Capacitive polarization (Helmholtz/Gouy-Chapman/Stern/...)
- Tertiary Current Distribution
 - Homogeneous
 - Convective & diffusive currents
 - Ion migration
 - Concentration dependency of diffusivity, etc.
 - Heterogeneous
 - Concentration overpotential
 - *Jacquet effects – ‘surface-occlusion saturation model’*
- Other
 - Carbon deposits/residues
 - Passive oxide formation

COMSOL® – Model Geometry & Parameters

Geometric Parameters

$$\begin{aligned}h_{peak} &= 5 \mu\text{m} \\w_{peak} &= 6 \mu\text{m} \\w_{spacing} &= 30 \mu\text{m} \\\delta_H &= 30 \mu\text{m}\end{aligned}$$

Physicochemical Parameters

$$\begin{aligned}D &= 10^{-10} \text{m}^2/\text{s} \\C_{sat} &= 0.4 \text{ M} \\\varphi &= 100\%\end{aligned}$$

Electrochemical Parameters

$$\begin{aligned}z &= 2 \\\alpha_{M,a} &= 1.5 \\\alpha_{M,c} &= 0.5 \\j_{o,M} &= 2 \text{ mA/cm}^2\end{aligned}$$

COMSOL® – Pulsed Waveforms

- Period (T) = On-time (t_{on}) + Off-time (t_{off})
- Frequency (ν) = $1/T$
- Duty Cycle (λ) = t_{on}/T
- Peak Current Density (j_p)
- Average Current Density ($j_a = \lambda j_p$)

Workpiece Boundary Condition

$$\left. \frac{\partial C}{\partial y} \right|_{y=0} = \begin{cases} -\frac{j_p}{nFD} & \text{during } t_{on} \\ 0 & \text{during } t_{off} \end{cases}$$

Concentration Profiles – Color Legend

★ Profile at end of on-time ** Profile at end of off-time

COMSOL® – Empirical Surface Saturation Model

$$j'_{0,M} = \Phi j_{0,M}$$

Results – Effect of Tertiary Current Distribution

Tertiary Current Distribution
ENABLED

Tertiary Current Distribution
DISABLED

Above Local Time-Averaged Concentration

Below Local Time-Averaged Concentration

Results – Effect of Tertiary Current Distribution

Tertiary Current Distribution
ENABLED

Tertiary Current Distribution
DISABLED

Results – Function of Feature Size

Summary

- *Empirical treatment of mass-transfer limitations with a surface-occlusion model successfully represents qualitative features of experimental observations*
- *Multiphysics modeling has the potential to provide guidance for pulsed-waveform selection*
- *Optimal pulse waveforms arise from a complex interaction of geometrical, physicochemical and electrochemical*

Acknowledgment

- This material is based upon work/resources supported by:
 - US Army SBIR Grant #W15QKN-18-C-0010
 - Commercial Partners
 - Faraday Corporate
- Contact Information:
 - Brian T. Skinn
 - Ph: +1 937 836 7749
 - Email: BrianSkinn@FaradayTechnology.com

Thank You!